

# iXware Enterprise Servers

## Minimal Hardware & Software Requirements

### Specific requirements

#### Fax Server requirements (Analogue and ISDN)

<b>Processor</b>	Intel Pentium IV, 2,4 GHz / AMD Athlon 3200+
<b>RAM</b>	2048 MB
<b>PCI Slots</b>	One or more free slots for the Fax/Voice boards. More free slots recommended. Please check the size of the board to be placed (full / half size, etc.). Mention on order form when ordering fax boards: <ul style="list-style-type: none"><li>• ISDN BRI-2M Half Size</li><li>• ISDN BRI-4M Half Size</li><li>• ISDN BRI-30M Full Size</li><li>• Analogue 2 Ports Half Size</li><li>• Analogue 4 Ports Full Size</li><li>• Analogue 8 Ports Full Size</li></ul> <i>(please notice the difference between PCI, PCIx and PCI Express)</i>

#### Fax Server requirements (FoIP)

<b>Processor</b>	Intel Pentium IV, 3GHz (dual core) AMD Athlon 3800+
<b>RAM</b>	4096 MB

*Please be advised that by using FoIP, the processing of faxes is carried out by the iXware Server (as opposed to by the DSP's on the hardware boards as in the case for ISDN and Analogue). FoIP requires Quality of Service on the network. Only offer FoIP in case a customer has its own switch in the LAN. Please consult iXware for FoIP requirements.*

#### Scanning server requirements

<b>Processor</b>	Intel Pentium IV, 3GHz (dual core) AMD Athlon 3800+
<b>RAM</b>	4096 MB

### General requirements

#### General hardware requirements

<b>Hard disk</b>	<ul style="list-style-type: none"><li>• 140GB</li><li>• NTFS (No formatted hard disk)</li><li>• First partition must be at least 50 GB</li></ul>
<b>DVD-Rom</b>	Preferred
<b>Ports</b>	<ul style="list-style-type: none"><li>• USB</li><li>• Remote USB (TCP/IP) for VMWare environments</li><li>• COM port (only when using GSM Wavecom device)</li></ul>
<b>Network</b>	Ethernet 100/1000 MB/s with a correctly configured TCP/IP protocol connected to the company network fixed IP address.
<b>PCI Slots</b>	One or more free slots for SMS device. More free slots recommended. Please check the size of the board to be placed (full / half size, etc.)

#### General software requirements

<b>Operating System</b>	<ul style="list-style-type: none"><li>• Windows 2003 (32 Bits) with R2</li><li>• Windows 2008 (32 &amp; 64 Bits) with R2</li><li>• Windows 7 Enterprise (32 &amp; 64 Bits)</li><li>• VM Ware 4 or higher / Hyper-V* / Xen</li><li>* Hyper-V doesn't support any kind of USB</li></ul>
<b>Other components</b>	<ul style="list-style-type: none"><li>• Internet Explorer 8</li><li>• Microsoft Internet Information Server</li><li>• .NET Framework 1.1</li><li>• .NET Framework 2 SP1</li><li>• .NET Framework 3.5</li><li>• .NET Framework 4.0</li><li>• .NET Framework 4.5</li><li>• Windows Installer 4.5</li></ul>

*For all server configurations you can choose either an USB dongle license or online license, except when virtualized (online).  
When using online license, a permanent connection to [license.ixware.com](http://license.ixware.com) is required.*

### Contact iXware

<b>Region</b>	<b>US &amp; Canada</b>
Contact	iXware North America
Phone number	+1 800 200 5521
Fax number	+1 734 293 2181
Website	<a href="http://www.ixware.com">www.ixware.com</a>
Email	<a href="mailto:nasales@ixware.com">nasales@ixware.com</a>

XEROX® and XEROX and Design® are trademarks of Xerox Corporation in the United States and/or other countries.

**Working together...  
getting results.**

**Together we can.**

[www.partner.xerox.com/xeroxbusinesspartners](http://www.partner.xerox.com/xeroxbusinesspartners)

